

# Novel 3D visualization of Laplace and Fourier transforms



Lars Bengtsson\*

Department of Physics, University of Gothenburg, Sweden

Submission: February 23, 2018; Published: March 12, 2018

\*Corresponding author: Lars Bengtsson, Department of Physics, University of Gothenburg, Sweden, Email: lars.bengtsson@physics.gu.se

## Abstract

This paper will demonstrate how to illustrate poles and zeros of a filter's transfer function as a 3D surface and how this facilitates an understanding of the relationship between the filter's amplitude response and the poles'/zeros' locations in s-space. The transfer function, in Laplace representation, is plotted as a function of the real and imaginary parts of the complex frequency s. This is exemplified for a Chebyshev-II low pass filter.

**Keywords:** Laplace transform; Poles; zeros; Transfer function; Bode plot; MATLAB; Filter

**Abbreviations:** PBL: Problem-Based Learning; LTI: Linear Time-Invariant

## Introduction

Transforms are probably one of the most versatile engineering tools as they facilitate a visualization of signals in frequency space. The complexity of the subject is widely recognized by students and teachers in engineering disciplines all over the world. It has been suggested that this is due to inconsistencies in the portrayal of transforms in standard textbooks [1]. In order to further the understanding of this abstract subject, different approaches have been suggested. In [2], it was suggested that signals be treated as vectors and transforms should be introduced as a scalar product used to decompose signals in order to disclose signal properties veiled in time space. Other approaches includes PBL (Problem Based Learning) [3] and "conceptual labs" [4,5] and also the use of the proper mathematical tools has been investigated [6].

In this mini review on transforms, a seminal way to graphically visualize poles and zeros that occur in Laplace (and z) transforms as 3D surfaces is suggested. This also facilitates a very elegant means to demonstrate graphically the relationship between the Laplace transform and the Fourier transform.

## Discussion

In engineering, Laplace transforms appear for example, as the transfer function in a linear, time-invariant (LTI) system:

$$H(s) = \frac{N(s)}{D(s)} \quad (1)$$

where N(s) and D(s) are polynomials in the complex frequency variable  $s = \sigma + j\omega$  [7]. The roots of the numerator are

called zeros and the roots of the denominator are called poles. These are singularities in s-space; at every zero the transfer function has a zero value and at the poles the transfer function has an infinite value. If the polynomial is of order n, there are exactly n poles or zeros, respectively.

Since the frequency variable s is complex, it is a function of both the real part and the imaginary part  $\omega$ ;  $H(\sigma) = H(\sigma, \omega)$  and  $|H(\sigma, \omega)|$  is a positive surface in s-space where the poles and zeros will appear as singularities in the surface. For example, let's consider a 3<sup>rd</sup> order Chebyshev2, low-pass filter with stop band ripple equal to 3 dB:

$$H(s) = \frac{3.0071s^2 + 4.0095}{s^3 + 3.7166s^2 + 2.3853s + 4.0095} \quad (2)$$

Figure 1 illustrates the Bode diagram of this filter.

The roots of the numerator and denominator are Zeros:  $0 \pm 1.1547j$  Poles:  $-0.1774 \pm 1.0776j$   $-3.3619$  The poles and zeros are illustrated in a 2D plot in (Figure 2).

This is the traditional way of illustrating poles and zeros. A seminal approach is suggested as follows:

Rewrite the transfer function in (2) as a function of two variables; the real part and the imaginary part;

$$H(\sigma, \omega) = \{3.0071(\sigma + j\omega)^2 + 4.0095\} / \{(\sigma + j\omega)^3 + 3.7166(\sigma + j\omega)^2 + 2.3853(\sigma + j\omega) + 4.0095\}$$

Next, we need to find the absolute value  $H(\sigma, \omega)$ . To this end, an online symbolic computational engine was used [8]. The

resulting expression is a square root fraction of polynomials (that is not reproduced here due to limited space). This expression is then used to create a mesh grid in MATLAB which is used to plot a 3D color map of the  $H(\sigma, w)$  function. This is illustrated in (Figure 3) and in (Figure 4) we have zoomed in part of the surface.

First of all we can easily identify the three poles and the two zeros in Figure 3 (compare with Figure 2). Notice what the poles and zeros look like in 3D; poles pull the surface out toward infinity and zeros nail the surface to the “floor”.

The important thing here is to understand how all the graphs in (Figures 1,2 & 3) relate to each other. The relationship between (Figures 2 & 3) should be clear by just comparing the locations of the poles and zeros in the two figures. Relating Figure 1 to the other plots is harder.




Figure 1: The Bode diagram of a third order Chebyshev-II filter.




Figure 2: The pole's and zero's location in the s-plane.




Figure 3: The poles' and zeros' location in a 3D plot.

The magnitude plot in (Figure 1) represents the filter's amplitude response, i.e. how it responds to harmonics of constant amplitude. In terms of the complex frequency variable  $s$ , this corresponds to frequencies with an imaginary part only. The real part of the complex frequency  $s = \sigma + jw$  represents harmonics with exponentially growing/decreasing amplitudes. Hence, the magnitude plot in (Figure 1) corresponds to the cross-section of the 3D surface at  $\sigma = 0$ . Also, in a Bode diagram, only positive frequencies are plotted. So, if we cut the 3D surface in Figure 3 at  $\sigma = 0$  (= real axis; already done in Figure 3)  $\omega = 0$  and at (the imaginary axis), the cross-section edge of the remaining 3D surface is exactly the amplitude response of the filter. In Figure 4 we have plotted the remaining surface and zoomed in on the cross-section edge. Compare the surface edge and the magnitude plot in (Figure 1); they agree exactly.

Conclusion

This work has suggested a seminal way to illustrate poles and zeros of a filter as a 3D plot with the objective of alleviating transform interpretation. From (Figures 3 & 4) the relationship between the pole/zero locations and the filter's amplitude response can be visualized.




Figure 4: Zooming in on the filter's amplitude response.

It should also be pointed out that since the cross-section edge in Figures 3 & 4 represents  $\sigma = 0$ , it also represents the magnitude of the Fourier transform, i.e. the Fourier transform of the filter's impulse response; the 3D representation of poles and zeros is also an excellent tool to demonstrate graphically the relationship between the Laplace transform and the Fourier transform.

The same exact technique could be applied to the z-transform with the only difference that the 3D surface should be cut along the unit circle to get the Fourier transform.

References

1. Lundberg KH, Miller HM, Trumper DL (2007) Initial Conditions, Generalized Functions, and the Laplace Transform. IEEE Control System Magazine 22-35.

2. Bengtsson L (2015) Teaching transforms: a vector approach. Int J Math Educ Sci Tech 46(5): 752-765.
3. Costa RJ, Honkala M, Lehtovuori A (2007) Applying the Problem-Based Learning Approach to Teach Elementary Circuit Analysis. IEEE Transactions on Education 50(1): 41-48.
4. Bernhard J, Carstensen AK (2002) Learning and teaching electrical circuit theory. PTEE2002: Physics Teaching in Engineering Education 163-178.
5. Bernhard J (2010) Insightful learning in the laboratory: Some experiences from 10 years of designing and using conceptual labs. Europ J Engin Edu 35(3): 271-287.
6. Evans BL, Karam LJ, West KA, McClellan JH (1993) Learning Signals and Systems with Mathematica. IEEE Transactions on Education 36(1): 72-78.
7. Lynn PA, Fuerst W (1998) Introductory digital signal processing. (2<sup>nd</sup> edn), John Wiley & Sons Ltd, Chichester, UK, p. 175.
8. <http://www.wolframalpha>.



This work is licensed under Creative Commons Attribution 4.0 License

### Your next submission with Juniper Publishers will reach you the below assets

- Quality Editorial service
- Swift Peer Review
- Reprints availability
- E-prints Service
- Manuscript Podcast for convenient understanding
- Global attainment for your research
- Manuscript accessibility in different formats  
**( Pdf, E-pub, Full Text, Audio)**
- Unceasing customer service

Track the below URL for one-step submission  
<https://juniperpublishers.com/online-submission.php>